


Model : **U04a**
 Description : DC Voltage to DC Voltage Transducer

Utilization:

The HOKKIM U04a is able to transduce input DC voltage of 0 to 100V into output DC voltage of 0 to 10V. The impedance of the output load should be greater than 100K Ω .

There is a zero adjustment to calibrate the output to 0V dc when input is at 0V dc. Another span adjustment to calibrate the output to 10V dc when input is maximum at 100V dc.



Technical Data

Supply Voltage	□115VAC □240VAC □12VDC □24VDC
Frequency	50~60Hz for AC Supply
Consumption	<2VA
Input Voltage	0 – 100V dc
Output Voltage	0 – 10V dc
Accuracy	±2% at full span
Output load Impedance	> 100K Ω
Indication	Green LED (Power)
Dielectric Strength Between:	
	Input & Supply Circuit 3KV Output & Supply Circuit 3KV

